Cat. No. 700-3407

ADDENDUM FOR 26-1183A BAR CODE READER

Note: This addendum and tape are for Tandy 200 owners only.

The Bar Code Reader owner's manual (Cat. No. 26-1183A) was originally written for use with the Model 100 Portable Computer. To make this manual compatible with your Tandy 200, all you will need to do is make the changes indicated below (an understanding of Tandy 200 operations is assumed):

1. Every reference to "Model 100" should be changed to "Tandy 200." (Just making a mental note of this change should suffice.)

2. Support of UPC bar codes is not included in this upgrade, so ignore all references to UPC codes in the manual. (Support for UPC bar codes will be provided by Bar Code Drivers, Cat. No. 26-3894.)

3. On page 9, the CLEAR statement at the top of the page should read:

   ```
   CLEAR 110, 60160
   ```

4. The example in the middle of page 9 should be changed to read as follows:

   ```
   Found: B3OF9
   Top  :  60160
   End  :  60656
   Exe. :  60320
   Ok
   ```

   Note: When paragraphs follow a screen sample like this one, be sure that the correct values indicated in this addendum are reflected in the paragraphs which follow the respective examples. Check this throughout the manual.

5. On page 10, the SAVEM command at the top of the page should read:

   ```
   SAVEM "B3OF9", 60160, 60656, 60320
   ```

6. In Example 1 on page 10, change lines 10 and 70 to read as follows:

```
10 CLEAR 110, 60160
70 CLOSE:CALL 60305
```

The rest of the program lines remain unchanged.

Refer to the Note in Item 4 above.

7. In the shaded box on page 11, change the CALL command to read:

```
CALL 60305
```

Refer to the Note in Item 4 above.

8. In Example 2 on pages 12 and 13, change lines 10, 20, 30, and 220 to read as follows:

```
10 MAXFILES=1:CLEAR 100,60160:CLEAR
20 F$(1)="B3OF9":F$(2)="PLESY"
30 CLS:PRINT:PRINT" 1. 3 of 9   2. Plessey"
220 CLOSE:CALL 60305:MENU
```

The rest of the program lines remain unchanged.

For "Floppy"

9. On page 21, near the bottom of the page, change the CLEAR statement to read:

```
CLEAR 110, 52992
```

10. The example near the top of page 22 should be changed to read as follows:

```
Found:  B3OF9D
Top  :  52992
End  :  53488
Exe. :  53152
Ok
```

Refer to the Note in Item 4 above.

11. On page 22, the SAVEM command near the bottom of the page should read:

```
SAVEM "B3OF9D.CO", 52992, 53488, 53152
```

12. In Example 1 on page 23, change lines 10 and 70 to read as follows:

```
10 CLEAR 110, 52992
70 CLOSE:CALL 53137
```

The rest of the program lines remain unchanged.

Refer to the Note in Item 4 above.

13. In the shaded box on page 24, change the CALL command to read:

```
CALL 53137
```

Refer to the Note in Item 4 above.

14. In Example 2 on page 25, change lines 10, 20, 30, and 220 to read as follows:

```
10 MAXFILES=1:CLEAR 100, 52992:CLEAR
20 F$(1)="B3OF9D":F$(2)="PLESYD"
30 CLS:PRINT:PRINT" 1. 3 of 9   2. Plessey"
220 CLOSE:CALL 53137:MENU
```

The rest of the program lines remain unchanged.

15. On page 30, step 2, change "UPC" to "B3OF9."

16. The screen shown below step 2 on page 35 is incorrect. It should be exactly the same as the screen at the top of page 37.

17. In the program listing for INVCRE.BA on page 38, change lines 20, 30, and 140 to read as follows:

```
20 MAXFILES=2:CLEAR 500,60160
30 RUNM "B3OF9"
140 CLOSE:CALL 60305:MENU
```

The rest of the program lines remain unchanged.

18. In the comment column for program line 20, at the bottom of page 39, change "61788" to "60160."

19. In the comment column for program line 30, at the top of page 40, change "UPC" to "B3OF9."

20. In the program listing for INVENT.BA on page 42, change lines 20, 30, and 140 to read as follows:

```
20 CLEAR 500,60160
30 RUNM "B3OF9"
140 CLOSE:CALL 60305:MENU
```

The rest of the program lines remain unchanged.

21. In the comment column for program line 20, at the top of page 44, change "61788" to "60160."

22. In the comment column for program line 30, at the top of page 44, change "UPC" to "B3OF9."

The tape included with this addendum contains the following files:

B3OF9.CO	B3OF9D.CO	INVENT.BA
PLESY.CO	PLESYD.CO	INVCRE.BA
READBC.BA	RDBCDV.BA	

These files are to be used exclusively with the Tandy 200.

Radio Shack
A Division of Tandy Corporation

875-9842